

cellcli

Show alerthistory for cell

```
dcli -g cell_group -l root cellcli -e list alerthistory
```

Show disk caching for griddisk disks

```
dcli -g cell_group -l root cellcli -e list griddisk attributes  
name,cachingpolicy,cachedBy
```

Disable caching of griddisk

```
alter griddisk RECOC1_CD_08_heiwccl08_man cachingpolicy='none'
```

Upgrade Infiniband Switch

```
export EXADATA_IMAGE_IBSWITCH_UPGRADE_VERSION=2.2.7_2  
cd patch_18.1.8.0.0.180906.1  
./patchmgr -ibswitches ../infini_group -upgrade -ibswitch_precheck
```

Online change WriteThrough to WriteBack Flash Cache

```
CellCLI>  
list griddisk attributes name, status, asmdeactivationoutcome  
alter griddisk all inactive  
drop flashcache  
alter cell shutdown services cellsrv  
alter cell flashCacheMode=WriteBack  
alter cell startup services cellsrv  
alter griddisk all active  
create flashcache all  
list cell attributes flashCacheMode  
list griddisk attributes name, status, asmmodestatus
```

Pinning tables in Flashcache

```
ALTER TABLE "SCHEMA_NAME"."TABLE_NAME" storage (cell_flash_cache keep);
```

Setting number of active cores on DB server

From:

<https://wiki.dewberry.co.za/> - **Shaun's Wiki**

Permanent link:

<https://wiki.dewberry.co.za/doku.php?id=exadata>

Last update: **2021/01/02 13:04**

