

cellcli

Show alerthistory for cell

```
dcli -g cell_group -l root cellcli -e list alerthistory
```

Upgrade Infiniband Switch

```
export EXADATA_IMAGE_IBSWITCH_UPGRADE_VERSION=2.2.7_2
cd patch_18.1.8.0.0.180906.1
./patchmgr -ibswitches ../infini_group -upgrade -ibswitch_precheck
```

Online change WriteThrough to WriteBack Flash Cache

```
CellCLI>
list griddisk attributes name, status, asmdeactivationoutcome
alter griddisk all inactive
drop flashcache
alter cell shutdown services cellsrv
alter cell flashCacheMode=WriteBack
alter cell startup services cellsrv
alter griddisk all active
create flashcache all
list cell attributes flashCacheMode
list griddisk attributes name, status, asmmodestatus
```

Pinning tables in Flashcache

```
ALTER TABLE "SCHEMA_NAME"."TABLE_NAME" storage (cell_flash_cache keep);
```

From:

<https://wiki.dewberry.co.za/> - Shaun's Wiki

Permanent link:

<https://wiki.dewberry.co.za/doku.php?id=exadata&rev=1578046494>

Last update: **2020/01/03 10:14**

